

VECTOR SCATTER INSTRUCTION CONTROL CIRCUIT AND
VECTOR ARCHITECTURE INFORMATION PROCESSING
EQUIPMENT

[0001]

5 FIELD OF THE INVENTION

The present invention relates to a vector architecture information processing equipment, and more particularly to a vector scatter instruction control circuit.

[0002]

10 BACKGROUND OF THE INVENTION

On a vector architecture information processing equipment, memory area data accessed by a vector instruction is not usually entered in a cache.

[0003]

15 The reason is that locality of reference generally does not well applies to data access by a vector instruction so that data accessed by a vector instruction, if entered in a cache memory, is swapped out immediately by other cache line data, and a cache hit ratio decreases.

[0004]

20 Also, on a vector architecture information processing equipment, there are provided some vector based memory access instructions, such as VST (vector store) /VLD (vector load) instruction in which a memory access address is defined by a start address and a distance of a vector data to be accessed.

25 [0005]

VLD instruction loads data from memory into a vector data storage area made of a plurality of words arranged in a vector unit, called "vector register" in accordance with memory access address defined as described above.

5 [0006]

Conversely, VST instruction stores data from a register into memory.

[0007]

In case of VST instruction, an address accessed by the instruction may be determined on an instruction issue stage. It is relatively easy to accomplish an improvement of performance, by controlling such an instruction as VLD instruction or scalar load instruction that follows VST instruction to be executed ahead of the VST instruction.

15 [0008]

On the other hand, with so-called "list vector" instructions, such as VGT (vector gather)/VSC (vector scatter) instructions, data stored in vector registers arranged in the vector unit is used as a memory address to be accessed so that the memory address to be accessed is identified only after the instruction gets to the vector unit, whereas the address is generally random.

[0009]

For the sake of better understanding of the present invention, a list vector instruction will be described with reference to FIG. 8.

25 [0010]

First, as shown in FIG. 8(a), VGT (vector gather) instruction loads data from memory in such a way that a memory data at an address VA (n) of a vector register Vy, is loaded into a corresponding element of the vector register Vx.

5 [0011]

As shown in FIG. 8(b), VSC (vector scatter) instruction stores data into memory in such a way that data of the vector register Vx is stored into a memory area of which address VA (n) is stored in a corresponding element of the vector register Vy.

10 [0012]

In contrast to vector memory access instructions, with a scalar memory access instruction, locality of reference generally applies to data accesses, as a result of which, such a system is usually adopted in which data accessed by the scalar memory access instruction is stored in a cache memory to make memory access latency being hidden.

15 [0013]

SUMMARY OF THE INVENTION

When a vector memory access instruction is issued to write data into memory on a vector architecture information processing equipment accommodated with a cache as described in the above, it is necessary to execute cache invalidation to ensure cache consistency in case that an address to be accessed is being entered in the cache, wherein the cache invalidation process generates a stall of a cache access instruction that follows the vector memory access instruction, which is a one of primary causes of degradation of performance.

20

25

[0014]

A cache invalidation process differs between VST (vector store) instruction and VSC (vector scatter) instruction.

[0015]

5 In case of VST instruction, a start address and a distance are determined when the instruction is issued so that with these two data relatively high-speed cache invalidation is realized. Furthermore, since memory access start address and end address of VST instruction can be calculated promptly, a scalar LD (load) instruction that follows VST
10 instruction, may be controlled to be executed ahead of the VST instruction if no address coincidence is detected between these two instructions.

[0016]

On the other hand, in case of VSC (vector scatter) instruction,
15 since an address to be accessed is determined only after the address is read from a vector register and, in addition, the address value is random, it is necessary to send an invalidation address from a vector unit to a cache invalidation control unit (see 4 in FIG. 1) in a scalar unit to invalidate cache data that matches the invalidation address.

20 [0017]

As a result, all memory access instructions that follow VSC instruction cannot be issued until this cache invalidation processing is completed. This causes degradation of performance.

[0018]

25 This problem will be described more in detail with reference to

FIGS. 6 and 7.

[0019]

First, in order to make description easy to understand, LDS instruction, which belongs to scalar load (cache access) instructions, will be described with reference to FIG. 7. As with VGT/VSC instruction, LDS instruction comprises four fields: OPC (operation code) and operands X, Y, and Z wherein a memory access address is calculated as $R_y + R_z$ and a resultant data M ($R_y + R_z$) that is read from memory area of an address $R_y + R_z$ is stored into register Rx.

[0020]

In FIG. 6(a), after VST (vector) instruction is issued, the cache is invalidated and, almost at the same time, data is written from the vector into memory.

[0021]

The LDS instruction following the VST instruction may be issued even with the cache being invalidated, unless access address of the LDS instruction overlaps with that of the VST instruction.

[0022]

On the other hand, referring to FIG. 6(b), with VSC (vector scatter) instruction, cache invalidation is performed when vector processing starts and an invalidating address is sent. In addition, since an address to be accessed immediately after VSC instruction is issued is not known and an address is random, LDS instruction that follows the VSC instruction is kept waiting in a hold state until cache invalidation is completed.

[0023]

As described above, all memory access instructions that follow the VSC instruction cannot be issued before cache invalidation is completed and this causes performance degradation.

5 [0024]

In view of the foregoing, it is an object of the present invention to provide a vector architecture processing equipment that prevents a following instruction from being delayed because of cache invalidation of a vector scatter instruction and that executes the following instruction before the vector scatter instruction to improve performance.

10 [0025]

To achieve the above object, in accordance with one aspect of the present invention is provided a circuit comprising:

means for detecting whether an overlap exists between an address to be accessed by an area-specified vector scatter instruction, which specifies a range of memory access address, and an address to be accessed by a memory access instruction that follows the area-specified vector scatter instruction; and

means for holding the memory access instruction that follows on which address coincidence is detected.

In accordance with one aspect of the present invention is provided a circuit for controlling vector scatter instruction wherein an area-specified vector scatter instruction specifying scattered areas is provided as an instruction set, comprising:

25 an address coincidence detection unit detecting if an address to

be accessed by the area-specified vector scatter instruction overlaps with an address to be accessed by a memory access instruction that follows the vector scatter instruction; and

a hold control unit holding the memory access instruction that
5 follows the vector scatter instruction if the addresses overlap.

In accordance with another aspect, is provided a vector architecture information processing equipment comprising:

a vector scatter address coincidence detection unit including:

registers for storing an area start address and an area end
10 address of an area-specified vector scatter instruction in which the area start address and the area end address are specified; and

a circuit for checking if an address to be accessed by a memory access instruction following the area-specified vector scatter instruction is within a scatter area defined by the area start address and the area end
15 address specified by the area-specified vector scatter instruction to outputs an address conflict signal if the address to be accessed by the following memory access instruction is within the scatter area, wherein an instruction issue control unit comprises a hold control circuit for holding said following memory access instruction upon receipt of an
20 address coincidence signal emitted from said vector scatter address coincidence detection unit.

In accordance with another aspect, the present invention provides a vector architecture information processing equipment comprising:

25 an instruction issue control unit decoding an instruction data to

direct an instruction operation;

a cache control unit receiving an address from said instruction issue control unit to control a cache;

a vector unit, on receipt of an execution directive when a vector instruction is issued from said instruction issue control unit sending write vector data to a memory and sending a cache invalidation address, if the vector instruction is an area-specified vector scatter instruction specifying an area start address and an area end address of a scatter area;

a cache invalidation control unit receiving the cache invalidation address from said vector unit to invalidate the cache; and

a vector scatter address conflict detection unit, on receipt of the area start address and the area end address of the area-specified vector scatter instruction from a register block accessed by said instruction issue control unit when the area-specified vector scatter instruction is issued from said instruction issue control unit,

detecting if an area specified by the area start address and the area end address overlaps with an address area to be accessed by a memory access instruction following the area-specified vector scatter instruction to activate an address coincidence signal for sending said signal to said instruction issue control unit if an address overlap is detected,

wherein said instruction issue control unit comprises a hold control circuit that holds the following memory access instruction in response to the activated address conflict signal from said vector scatter

address conflict detector.

The hold control circuit preferably does not hold the following memory access instruction if the address coincidence signal from said vector scatter address coincidence detection unit is inactive. The hold control circuit holds the following memory access instruction until a cache invalidation end notification is received from said cache invalidation control unit.

The vector scatter address coincidence detection unit preferably comprises:

10 a first comparator that compares the address to be accessed by the following memory access instruction with the area start address specified by the area-specified vector scatter instruction and, if the address to be accessed by the following memory access instruction is equal to or larger than the area start address, outputs an active signal;

15 a second comparator that compares the address to be accessed by the following memory access instruction with the area end address specified by the area-specified vector scatter instruction and, if the address to be accessed by the following memory access instruction is equal to or smaller than the area end address, outputs an active signal;

20 and

a logical circuit that activates the address conflict signal and outputs the signal if both output signals from said first comparator and the output from said second comparator are active.

25 In an operand of the area-specified vector scatter instruction is included a predetermined field for specifying two registers in which the

scatter area start address and the scatter area end address are respectively specified, said two registers being included in said register block.

Still other objects and advantages of the present invention will become readily apparent to those skilled in this art from the following detailed description, wherein only the preferred embodiment of the invention is shown and described, simply by way of illustration of the best mode contemplated of carrying out this invention. As will be realized, the invention is capable of other and different embodiments, and its several details are capable of modifications in various obvious respects, all without departing from the invention. Accordingly, the drawing and description are to be regarded as illustrative in nature, and not as restrictive.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a diagram showing a configuration of an embodiment of the present invention.

FIG. 2 is a diagram showing a configuration of an instruction issue control unit and a VSC address conflict detector in the embodiment of the present invention.

FIG. 3 is a diagram showing VSC instruction in the embodiment of the present invention.

FIG. 4 is a diagram showing an operation of the embodiment of the present invention.

FIG. 5 is a diagram showing an operation of the embodiment of the present invention.

FIG. 6 is a diagram showing a processing of VSC instruction and following LDS instruction.

FIG. 7 is a diagram showing a processing of LDS instruction.

FIG. 8 is a diagram showing conventional VGT instruction and VSC instruction.

[0026]

PREFERRED EMBODIMENTS OF THE INVENTION

An embodiment of the present invention will now be described.

An embodiment of the present invention comprises a vector scatter
 10 (VSC) address coincidence detection unit that comprises a plurality of registers in which an area start address and an area end address of an area specified by an area-specified vector scatter instruction are stored; and a circuit that detects if memory address specified by the area-specified vector scatter instruction overlaps with memory address to be
 15 accessed by a memory access instruction following the area-specified vector scatter instruction, wherein an instruction issue control unit comprises a hold control circuit that holds a following memory access instruction that specifies memory address coincides with address specified by the area-specified vector scatter instruction.

20 [0027]

More specifically, in a preferred embodiment of the present invention, a vector architecture information processing equipment comprises:

an instruction issue control unit (1) that decodes instruction
 25 data and directs an instruction operation;

a cache control unit (2) that receives an address from the instruction issue control unit (1) for controlling a cache (for example, cache update for scalar memory access instructions);

a vector unit (6) that receives an execution directive when a vector instruction is issued from the instruction issue control unit (1) and, if the vector instruction is an area-specified VSC instruction (vector scatter instruction) specifying an area start address and an area end address of a scatter area, sends vector data to be stored onto a memory (7) and, at the same time, sends a cache invalidation address;

a cache invalidation control unit (4) that receives the cache invalidation address from the vector unit (6) for invalidating the cache; and

a VSC address conflict detection unit (3) that receives the area start address and the area end address specified by the area-specified VSC instruction from a register block (5) when the area-specified VSC instruction is issued from the instruction issue control unit (1), detects if an area specified by the area start and end addresses overlaps with an address area to be accessed by a memory access instruction following the area-specified VSC instruction, activates an address conflict signal if an address overlap is detected, and sends the signal to the instruction issue control unit (1).

The instruction issue control unit (1) comprises a hold control circuit (105 in FIG. 2) that holds the following memory access instruction in response to the activated address conflict signal from the VSC address conflict detection unit (3).

[0028]

According to the present invention, the area-specified VSC instruction has an op-code and X, Y, and Z fields, where two registers from a register block are specified for the Z field and a start address and
5 an end address of a scatter area are respectively specified in these two registers.

[0029]

The embodiment of the present invention will be described more in detail, using an example with reference to the drawings. FIG. 1,
10 illustrates a basic configuration of one embodiment of the present invention.

[0030]

Referring to FIG. 1, a vector machine of the embodiment of the present invention comprises a scalar processor, a vector unit 6, and a
15 memory 7. The scalar processor comprises an instruction issue control unit 1, a register block 5, a cache control unit 2, a VSC address coincidence detection unit 3, and a cache invalidation control unit 4.

[0031]

The instruction issue control unit 1 decodes instruction data
20 read from the memory 7 via a signal line 71 to request instruction execution.

[0032]

The instruction issue control unit 1 sends an address to the cache control unit 2 and the VSC (vector scatter instruction) address
25 coincidence detection unit 3 via a signal line 12, wherein the cache

control unit 2 and the VSC address coincidence detection unit 3 both receiving the address, execute controlling cache access and checking VSC address coincidence respectively.

[0033]

5 The instruction issue control unit 1 controls read form and write to the register block 5 respectively via signal lines 15 and 51.

[0034]

10 If scalar loading from the instruction issue control unit 1 misses , the cache control unit 2 requests cache refill data via a signal line 27 and receives the data from the memory 7 via a signal line 72.

[0035]

15 When a scalar store instruction is issued, a cache control by the cache control unit 2 is performed based on store-through algorithm, whereon in case that a cache hit occurs the cache control unit 2 rewrites cache data and always writes the data in the memory 7.

[0036]

20 When a vector instruction is issued, the instruction issue control unit 1 sends an execution directive to the vector unit 6 via a signal line 16. At this time, in case that the vector instruction is VSC instruction, the vector unit 6 sends vector data to be written to the memory 7 via a signal line 67. In addition, the vector unit 6 sends a cache invalidation address to the cache invalidation control unit 4 via a signal line 64.

[0037]

25 In addition, when a VSC instruction is issued, a start address

and end address of the VSC instruction are sent from the register block 5 to the VSC address coincidence detection unit 3 via a signal line 53. The VSC address coincidence detection unit 3 checks if an address area specified by the instruction overlaps with that specified by a following memory access instruction to send an address coincidence signal to the instruction issue control unit 1 via a signal line 31 in case that an address overlap is detected.

[0038]

Next, specifications of an area-specified VSC instruction proposed newly by the present invention will be described with reference to FIG. 3.

[0039]

As shown in FIG. 3, instruction field of the area-specified VSC instruction is divided into four as described above: OPC (operation code), X, Y, and Z. The area-specified VSC instruction differs from the normal VSC instruction in that the Z field specifies two registers in the register block 5, R_n and R_{n+1} , which respectively specify a start address and an end address of a scatter area. The X and Y fields of the VSC instruction are respectively used to specify the number of a vector register in the vector unit 6.

[0040]

FIG. 2 illustrates a configuration of the instruction issue control unit 1, the register block 5, and the VSC address coincidence detection unit 3 of the embodiment of the present invention.

[0041]

Referring to FIG. 2, instruction data supplied via the signal line 71 is once stored in an instruction cache 101 and then stored in the four fields, OPC (instruction code), X, Y and Z, of a D stage register 102.

5 [0042]

After that, the instruction code, X field, and Y field are moved to an EE stage register 103. At the same time, the operand data is read from a register 50 of the register block 5 into registers Y data ee and Z data ee in the EE stage register 103.

10 [0043]

In the case of LDS instruction, information in the EE stage register 103 is moved to an EC stage register 104 that follows. At the same time, an address calculated by an AAD (address adder) 115 are stored in an address ec (register) for use in accessing the cache. The output of the address ec (register) is supplied to the cache control unit 2 as the address signal 12 in FIG. 1 and to the VSC address coincidence detection unit 3.

[0044]

In the case of the area-specified VSC instruction newly provided by the present invention, VSC start address and end address read via the Z data ee (latch) in the EE stage are stored, respectively, in VSC start address ec and VSC end address ec in the EC stage. Note that a signal H supplied from an HLD (hold) control unit 105 to the VSC start address ec and the VSC end address ec, is a signal used to direct the VSC start address ec and the VSC end address ec to hold data.

20

25

[0045]

After that, data held in the VSC start address ec and the VSC end address ec, strobed by the a VSC issue signal 13 from the HLD control unit 105, is set in the VSC start address eb (latch) and the VSC
5 end address eb (latch) in the EB stage.

[0046]

The information is retained until the next area-specified VSC instruction is issued.

[0047]

10 The VSC address coincidence detection unit 3 comprises a comparator 301, a comparator 302, and a logical product circuit 303. The comparator 301 compares a value of the address ec that latches an access address of a memory access instruction that follows with a value of the VSC start address eb to output an activated output signal, if the
15 address to be accessed by the following memory access instruction is equal to or larger than the VSC start address. The comparator 302 compares a value of the address ec with a value of the VSC end address eb to outputs an activated output signal, if the address to be accessed by the following memory access instruction is equal to or smaller than the
20 VSC end address. When both output signals supplied from the comparator 301 and the comparator 302 are active, the logical product circuit 303 provides an activated address coincidence signal 31 to the HLD control unit 105.

[0048]

25 If the address to be accessed by the following LDS instruction

that is issued immediately following the area-specified VSC instruction overlaps with the scatter area of the VSC instruction, the VSC address coincidence signal 31 is activated and sent to the HLD control unit 105. In response to this signal, the HLD control unit 105 activates (turns on) the ECHLD signal. This signal remains in an activated state (on state) until a cache invalidation end signal 41 output from the cache invalidation control unit 4 is turned on (until cache invalidation processing is completed). The following LDS instruction is held in the EC stage of the instruction issue control unit 1.

10 [0049]

If the LDS instruction being kept waiting in the EC stage is followed by another instruction, the HLD control unit 105 turns on the EEHLD signal or the DHLD signal to keep the following instruction waiting in the EE stage or in the D stage.

15 [0050]

A register update control unit 111 shown in FIG. 2 controls update of the register 50 in the register block 5, for example, controls an avoidance of known WAW (write after write) hazard. In case of VSC instruction, an output from the X/Y ec of the EC stage register 104 indicates a vector register number, which is supplied to the vector unit 6 via the signal line 16.

[0051]

Next, operation timings of the area-specified VSC instruction and immediately following LDS instruction in the embodiment of the present invention will be described with reference to FIGS. 4 and 5. In

those two examples, it is assumed that a cache hit occurs on the following LDS instruction.

[0052]

FIG. 4 illustrates a timing operation when an area (scatter area) specified by the area-specified VSC instruction does not overlap with an address to be accessed by the immediately following LDS instruction, that is, when an address coincidence does not occur. Note that, in FIGS. 4 and 5, DD, EE, EC, and EB correspond respectively to the D stage, EE stage, EC stage, and EB stage (VSC start address eb, VSC end address eb) in the instruction issue control unit 1 shown in FIG. 2.

[0053]

The area-specified VSC instruction, which must read registers twice (R_n and R_{n+1}) specified in the Z operand (Z_d), is divided into two (VSC1st and VSC2nd in FIG. 4) in the D stage. A increment circuit (+1) is a control circuit for reading the registers twice (R_n and R_{n+1}).

[0054]

In timing 3 and 4, the VSC instruction issue signal 13 is asserted. At this time, the start address and the end address are stored, respectively, in the VSC start address eb and the VSC end address eb.

[0055]

After that, when the LDS instruction is issued in timing 5 in the EC stage, cache data is read in timing 6 and the cache data is stored into a WDR (write data register) in register block 5 in timing 7. In timing 8, contents of the WDR are written in the register 50 to finish an execution of the LDS instruction. WAR in the register block 5 is a write

address register that is used to select a register from a plurality of registers in the register 50 (register file).

[0056]

Next, with reference to FIG. 5, an description is done
 5 concerning an operation performed when an area specified by the VSC instruction overlaps with an address to be accessed by the following LDS instruction, that is, an operation performed when an address coincidence occurs. Difference between an operation shown in FIG.5 and that shown in FIG. 4 begin to appear from timing 5 at which the
 10 signal indicating that VSC addresses coincidence signal is turned on in FIG.5.

[0057]

After that, the LDS instruction is held in the EC stage with the ECHLD signal being kept in a on state until the cache invalidation end
 15 signal 41 is turned on in timing 7.

[0058]

Then, as in case that address does not coincide, a result of the LDS instruction is written on the register 50 via the WDR in the register block 5.

20 [0059]

In the embodiment of the present invention, the instruction control circuit obtains information on the memory area to be accessed by the area-specified VSC instruction from a programmer (that is, from a program coded by the programmer). This allows LDS instruction that
 25 follows to be executed ahead of the area-specified VSC instruction, as a

result of which significantly improves performance. A effect of the embodiment of the present invention will be described more in detail with reference to FIG. 6.

[0060]

5 First, with a VST instruction, an area to be accessed is determined at an instruction issue time. Therefore, the cache may be invalidated immediately to allow following LDS instruction to be executed ahead of the VST instruction. If it is found that the following instruction may be executed before the preceding instruction, the LDS
10 instruction may be executed even on a period on which cache invalidation is under way.

[0061]

On the other hand, in a conventional vector machine, since memory area to be accessed by VSC instruction is not determined when
15 the instruction is issued and in addition, is random, LDS instruction that follows cannot be executed before the VSC instruction and must be delayed until cache invalidation is completed.

[0062]

With the present invention, it is possible to control LDS
20 instruction that follows to be executed ahead of the preceding VSC instruction as if the VSC instruction was a VST instruction.

[0063]

With the conventional vector data processing unit, it is necessary for the following LDS instruction, an access address of which
25 is arbitrary one, to wait from issue time of the VSC instruction to a time

of completion of cache invalidation process.

[0064]

On the other hand, in accordance with the present invention this wait time is eliminated when no address coincidence occurs, as a
5 result of which significantly improves performance of LDS instruction that is issued with a extremely high frequency.

[0065]

The meritorious effects of the present invention are summarized as follows.

10 As described above, with the present invention, by acquiring information on areas to be accessed by an area-specified VSC (vector scatter) instruction from a program, LDS instruction that follows the area-specified VSC instruction may be executed before the area-specified VSC instruction to improve significantly processing
15 performance. The reason is that the data processing unit according to the present invention provides means for detecting whether a address coincidence occurs between an address to be accessed by the VSC instruction, which specifies scattered areas, and an address to be accessed by the following instruction and means for holding the
20 following memory access instruction when an address conflict occurs.

It should be noted that other objects, features and aspects of the present invention will become apparent in the entire disclosure and that modifications may be done without departing the gist and scope of the present invention as disclosed herein and claimed as appended
25 herewith.

Also it should be noted that any combination of the disclosed and/or claimed elements, matters and/or items might fall under the modifications aforementioned.

11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2210
2211
2212
2213
2214
2215
2216
2217
2218
2219
2220
2221
2222
2223
2224
2225
2226
2227
2228
2229
2230
2231
2232
2233
2234
22